

PORTABLE/BASE STATION

FT-8800R/E

E for European Version

144/430_{MHz}
DUAL BAND



ACTUAL SIZE

*Simulated LCD display

29/50/144/430_{MHz}
QUAD BAND



FT-8900R

YAESU
Choice of the World's top DX'ersSM

FT-8800 Series

HIGH PERFORMANCE

■ WIDE FREQUENCY COVERAGE

The FT-8800 series provides extended receiver coverage beyond the Amateur bands, so you can keep informed of communications activities in the public safety, commercial, aircraft, and government communications ranges.

■ INDEPENDENT TWO-CHANNEL OPERATION

The FT-8800 series operates as two radios in one, with either 144 MHz or 430 MHz as the "Main" TX/RX band, with simultaneous monitoring of the other band. Each band has its own Volume and Squelch controls, and you can configure your FT-8800 series for VHF-VHF or UHF-UHF operation, too!



■ HIGH POWER OUTPUT

To get your message through when it counts, the FT-8800 series puts out a full 50 Watts of power on the 144 MHz band, and 35 Watts on 430 MHz. A thermal sensor monitors heat sink temperature, engaging the rear panel's cooling fan only when needed.



HIGH	MID1	MID2	LOW
50W/35W(430MHz)	20W	10W	5W

■ OVER 1000 MEMORY CHANNELS

The FT-8800 series provides a wide variety of memory resources, including 512 "regular" memories each band, Five "Home" channels for favorite frequencies, Ten sets of band-edge memories each band, and six "Hyper Memories" which store complete sets of transceiver operating status.



■ LARGE, EASY-TO-READ LIQUID CRYSTAL DISPLAY (LCD)

Affording easy viewing from a wide variety of viewing angles, the LCD of the FT-8800 series features Yaesu's renowned Omni-Glow™ display illumination, with four illuminations levels available for different operating environments.

■ CROSS-BAND REPEAT CAPABILITY

For emergency work, or to extend the range of a hand-held unit, the FT-8800 series includes Cross-Band Repeat capability, similar to that pioneered on our popular FT-8100 series Dual Band FM Mobile!

■ VERSATILE SCANNING CAPABILITY

The FT-8800 series lets you scan the memories, the entire operating band, or a portion of the band. The transceiver will stop on signals encountered during the scan, resuming the scan after a time delay or after the carrier drops out. During band scanning, you may configure the FT-8800 series to remain within the current band, or hop to the other band, once the band edge is reached. Dual-frequency "Priority Channel" operation is also provided. And the Programmable Memory Scan feature allows you to set up sub-band limits, so you won't waste time scanning or tuning in the SSB/CW portions of the bands.

■ 50-TONE CTCSS/104-TONE DCS (DIGITAL CODE SQUELCH) TONE SYSTEMS

Providing excellent performance even under difficult link conditions, Yaesu's 50-tone sub-audible CTCSS and 104-tone DCS signaling systems ensure that you have full access to repeater and remote-base inputs, and the built-in CTCSS/DCS decoders allow silent listening on busy channels. Plus you get Tone Search Scanning, which will scan for the tone being received on an incoming signal, allowing you to match tones quickly when operating on a new repeater system.

■ ARTS™ (AUTO-RANGE TRANSPONDER SYSTEM)

Included in the FT-8800 series is Yaesu's exclusive ARTS™ feature which provides a "hand-shake" with other ARTS™-equipped stations during emergency work. If an "out-of-range" conditions exists with, for example, a low-power hand-held unit, ARTS™ will alert the FT-8800 series user so the hand-held's operator can be advised to move to a better location.

■ USER-PROGRAMMABLE MICROPHONE KEYS

Four programmable keys on the microphone allow you one-touch access to your favorite command functions. The commands available from the microphone replicate the corresponding front panel key functions, and include Band Change, VFO/Memory switching, Home Channel access, 1 MHz frequency steps, Power Output selection, Repeater Reverse, and CTCSS/DCS setup.

■ ONE-TOUCH BAND-PATTERN "HYPER MEMORY" FEATURE

To save valuable time when operating a transceiver with the capability of the FT-8800 series, the "Hyper Memory" feature allows you to store a complete set of configuration data for the two bands on which you're operating. Hyper Memory will store not only frequency and tone data, but also Automatic Repeater Shift status, Packet parameters, Scanning mode, and VFO tracking configuration.



SPECIFICATIONS

General

Frequency Range:	RX: 108.000 - 520 MHz, (USA Version) 700 - 999.995 MHz (Cellular Blocked)
	TX: 144.000 - 146.000 MHz (or 144.000 - 148.000 MHz), 430.000 - 440.000 MHz (or 430.000 - 450.000 MHz)
Frequency Steps:	5/10/12.5/15/20/25/50 kHz
Operating Modes:	F3, F2, F1
Antenna Impedance:	50 Ω , unbalanced (Antenna Duplexer built-in)
Frequency Stability:	± 5 ppm @ 14° F ~ +140° F (-10 °C ~ +60 °C)
Operating Temperature Range:	-4° F ~ +140° F (-20 °C ~ +60 °C)
Supply Voltage:	13.8 VDC ($\pm 15\%$), negative ground
Current Consumption (Approx.):	RX: 0.5 A (Squelched) TX: 8.0 A (430 MHz), 8.5 A (144 MHz)
Case Size (W x H x D):	5.5" x 1.6" x 6.6" (140 x 41.5 x 168 mm) (w/o knobs & connectors)
Weight (Approx.):	2.2 lb (1 kg)
Transmitter	
Power Output:	50/20/10/5 W (144 MHz), 35/20/10/5 W (430 MHz)
Modulation Type:	Variable Reactance
Maximum Deviation:	± 5 kHz
Spurious Radiation:	Better than -60 dB
Modulation Distortion:	Less than 3%
Microphone Impedance:	2 k Ω
DATA Jack Impedance:	10 k Ω
Receiver	
Circuit Type:	Double-conversion superheterodyne
Intermediate Frequencies:	45.05 MHz/450 kHz (Left band), 47.25 MHz/450 kHz (Right band)
Sensitivity (for 12dB SINAD):	Better than 0.2 μ V
Squelch Sensitivity:	Better than 0.16 μ V
Selectivity (-6dB/-60dB):	12 kHz/30 kHz
Maximum AF Output:	2 W @ 8 Ω for 5% THD
AF Output Impedance:	4-16 Ω

Specifications are subject to change without notice, and are guaranteed within the 144, and 430 MHz amateur bands only. Frequency ranges will vary according to transceiver version; check with your dealer.

OPTIONS

 MH-42B6JS Hand Microphone	 MLS-100 High-Power External Speaker	 YSK-8900 Separation Kit	 MMB-60 Quick Release Mobile Mounting Bracket	 MEK-2 Microphone Extension Kit (for use with Yaesu 8-pin Microphones)	 CT-39A Packet Interface Cable	 FP-1023 (U.S.A. only) AC Power Supply (25 A)	 FP-1030A AC Power Supply (30 A)
--	--	--	---	--	--	---	--

About this brochure: we have made this brochure as comprehensive and factual as possible. We reserve the right, however, to make changes at any time in equipment, optional accessories, specifications, model numbers, and availability. Precise frequency range may be different in some countries. Some accessories shown herein may not be available in some countries. Some information may have been updated since the time of printing; please check with your Authorized Yaesu Dealer for complete details.



— VERTEX STANDARD CO., LTD. —

4-8-8 Nakameguro, Meguro-ku, Tokyo 153-8644, Japan

For the latest Yaesu news, visit us on the Internet:
<http://www.vxstd.com>

— VERTEX STANDARD —

<http://www.vxstdusa.com>

Email: amateursales@vxstdusa.com

Phone 714/827-7600; Fax 714/827-8100

US Headquarters

10900 Walker Street, Cypress, CA 90630, U.S.A.

International Division

8350 N.W. 52nd Terrace, Suite 201, Miami, FL 33166, U.S.A.

— YAESU EUROPE B.V. —

P.O. Box 75525, 1118 ZN Schiphol, The Netherlands

— YAESU UK LTD. —

<http://www.yaesu.co.uk>

Email: sales@yaesu.co.uk

Unit 12, Sun Valley Business Park, Winnall Close
Winchester, Hampshire, SO23 0LB, U.K.

— VERTEX STANDARD HK LTD. — <http://www.vxstd.com.hk>

Unit 5, 20/F., Seaview Centre, 139-141 Hoi Bun Road,
Kwun Tong, Kowloon, Hong Kong